

Technical Bulletin
SIRIUS Stiletto 2 – Software Release 2.0.4
August 11, 2008

SIRIUS has made a few key improvements to the Stiletto 2 software recently. These have been made available to all subscribed Stiletto 2 units through a software upgrade. Downloading this update will ensure that Stiletto 2 continues to operate at peak efficiency.

Taking advantage of these enhancements is fast and easy - just follow the directions below to download and install the new v 2.0.4 software.

What's Included in the Release

Recently Sirius has made some changes to the broadcast systems and programming channel lineups. The 2.0.4 release together with the 14.94 baseband firmware help ensure that the Stiletto 2 portable will continue to work properly.

This update also contains changes to the channel logo and channel announcement assets. This assures that channels which have been moved, or new channels added to our programming lineup, will display the correct information.

How to Get this Release

There are two ways to update Stiletto 2 with this software:

Option 1: Updating over WiFi:

Subscribers may update Stiletto 2 over an accessible WiFi network by following these steps:

1. Turn on the Stiletto 2 and press the **HOME** button
2. Use the **MEDIA DIAL** to scroll to Internet Radio
3. Press the **SELECT** button to connect to Internet Radio
4. Tune to your favorite station and let it play one to two hours
5. The software will download automatically. Once received, follow the on-screen prompts to complete the update.

Option 2: Updating using My SIRIUS Studio™:

Subscribers without WiFi access may update using the USB cable and **My SIRIUS Studio™** software supplied with their radio. This will require a Windows PC with an active internet connection:

NOTE: If you have a microSD™ memory card installed, we recommend removing it before starting the update.

1. Launch **My Sirius Studio™** on your computer. Be sure you are running version 1.5 or higher. You can download the latest version of My Sirius Studio here.
2. Connect Stiletto 2 to your computer using the USB cable supplied with your device or place the Stiletto in a USB connected Home Dock and press the 'sync' button.
3. When the picture of Stiletto has appeared in the My SIRIUS Studio software window, click on the gear icon next to the device or go to **File→ Device Settings→ Check for Software Update**.
4. Follow the instructions that appear in My SIRIUS Studio™ and on your Stiletto's screen to complete the update.
5. After disconnecting Stiletto from your PC, switch off Stiletto by holding down the power switch. When Stiletto has completely shut down, restart it by using the power switch.
6. Once it has restarted, reconnect the Stiletto to your PC. Click on the gear icon in My SIRIUS Studio to check for additional updates. If one is available, follow the instructions that appear to download the additional updates. If there is no update available, skip to step 8 to verify the software version on your device.
7. After downloading any additional updates, power down your Stiletto by holding down the power switch. When it is completely shut down, restart Stiletto. When Stiletto has restarted, tune to **Satellite Radio** mode. Any additional updates will install automatically.
8. Following the update process, verify the software version on your device by using the Media Dial to go to **Settings → Device→ Device Info**. Updated units will display the following versions in **Device Info** (Fig.1).

Model	ZAP	OS	Bootloader	Baseband
Stiletto 2	2.0.4.64538	2.0.3.54429	varies	00.14.94



Fig. 1

For additional questions regarding your Stiletto 2 or the SIRIUS service, please refer to the product manuals. You can also reach the dedicated Stiletto Technical Support Team

at 1-800-869-5364 from 6:00 AM to 1:00 AM Eastern Time Monday through Saturday, or by email at customercare@sirius-radio.com.